Yealink W52P IP Phone

Quick Reference Guide



No.	Item	Description
1	Receiver	Receives audio
2	LCD Screen	Shows information about calls, messages, softkeys, time, data and other relevant data
3	Soft Keys	Access the function directly. It depends on the operation situation
4	Speakerphone	 Switches among receiver, headset and handsfree modes Answers an incoming call Places a call in handsfree mode
5	Headset Connector	Allows you to connect a standard 2.5mm earphone
6	Off-hook Key	Answers an incoming callEnters the redial calls listPlaces a call in earpiece mode
7	Keypad	Provides digits, letters and special characters
8	*/Music Icon	 Enters the star symbol and other special characters Switches the silent mode to On or Off
9	Redirect Key	Transfers a call to another party
10	Microphone	Picks up audio
11	Mute	Toggles mute feature on or off
12	#/Lock Icon	Enters the pound symbolLocks or unlocks the handset keypadSwitches the input method
13	On-hook Key/Power Key	 Press to return to the previous screen Long press to return to idle screen Press to turn the handset on Long press on the idle screen to turn the handset off Cancels actions or ends a call Rejects an incoming call
14	Message Key	Indicates a new voice mail or missed callAccesses voicemail or the missed call list
15	Up/Down Left/Right	Move the cursorAct as shortcuts

Adjust the ringer volumeSwitch among the values

Cursors



Answer a call

To answer a call using the earpiece:

1. Press \(\sigma \) or the Accept soft key.

To answer a call using the speakerphone:

1. Press \leq .

To answer a call using the earphone:

 With an earphone connected, press the Accept soft key.

Answering When in Another Call:

If you are during an active call, an incoming call

arrives on the handset, do the following:

- 1. Press to select the incoming call.
- 2. Press , , or **OK** or the Accept soft key. The incoming call is answered, and the original call is placed on hold.

Make a call

To place an external call via the handset:

- 1. Enter the desired number using the keypad.

If you do not select a line, the handset uses the default outgoing line to dial out.

2. Press , , or **OK** to dial out. You can place at most two calls on your handset. You can also place an internal call during an external call.

Place a call on hold and resume

To place a call on hold:

 Press the Options soft key during a call, and then select Hold. The call is placed on hold, and the icon is displayed on the LCD screen.

To resume a hold call: Do one of the following:

- Press the Resume soft key
- Press □ .
- Press 📞 .

Call transfer

Pick up any call within your office (if configured to individual team members)

To perform a blind transfer:

- 1. Press the Options soft key during a call, and then select Transfer. You can also press directly.
- 2. Enter the number or select the handset you want to transfer the call to.
- 3. Press TRAN or the Transfer soft key. The call is connected to the number or the handset you specified.

To perform a semi-attended transfer via the handset:

- 1. Press the Options soft key during a call, and then select Transfer. You can also press directly.
- 2. Do one of the following:

Enter the number or select the handset you want to transfer the call to.

- Press & , \triangleleft or **OK** to dial out.
- Press the Directory soft key, and then select the desired contact.
- Press , , or OR the Call soft key. If both the office number and the mobile number of the contact are stored, select the desired number and then press "," to dial out.
- 3. Press TRAN or the Transfer soft key to complete the transfer when receiving the ring-back.

Hold/Resume

You can place an active call on hold. At any time, at most one active call can be in progress on your handset.

You can answer or make another call while placing the original call on hold. To put a call on Hold, press the Options soft key and then select Hold.

To resume the call. press the Resume soft key. If 2 calls are on hold at the same time you can use the Up/Down arrow or the Swap soft key to swap between the two calls.